# **ONE PUSH CLEANERS**







FOA-00016-25 One Push Cleaner for 2.5mm E2000, SC, ST & FC connectors

## DESCRIPTION

One Push Cleaner is designed to perform cleaning on the ferrule end surfaces inside various types of adapter or port without nicking or scratching the end face. It uses the mechanical push action to rotate the cleaning tip made from lint-free material in reel form to achieve an optical grade cleaning.

## **FEATURES**

- Cleans connectors or jumper ferrule end surface in adapters or ports
- Compliant with EU/95/2002/EC Directive (RoHS)
- Single action cleaning
- More than 800 cleaning cycles
- Very low cost per cleaning
- Effective on a variety of contaminates

### **APPLICATIONS**

- Fiber network patch panels and assemblies
- Outdoor FTTX applications
- Transceiver and cable assembly production
- Server, switches, routers and OADMS with SC and LC interface
- Laboratories

## **SPECIFICATIONS**

	Φ1.25mm One Push Cleaner	Φ2.5mm One Push Cleaner
Model	FOA-00016-12	FOA-00016-25
Dimension (mm)	13W x 13H x 80L	13W x 13H x 80L
Extended Dimension (mm)	115L	115L
Connector/Adapter Type	MU, LC	SC, FC, ST, E2000
Cleaning Cycle	800 times	800 times

#### **ORDERING INFORMATION**

Part No	Description	
FOA-00016-12	One Push Cleaner for 1.25mm LC & MU connectors or ports	
FOA-00016-25	One Push Cleaner for 2.5mm E2000, SC, ST & FC connectors or ports	

Note : Specifications are subject to change without notice

